

6/parts

1

DESCRIPTION

MEMORY CIRCUIT AND COHERENT DETECTION CIRCUIT

5 Technical Field

The present invention relates to a memory circuit and coherent detection circuit.

Background Art

10 In a CDMA (Code Division Multiple Access)-based mobile communication, the amplitude and phase of an information symbol fluctuate under the influence of Raleigh fading.

15 A "coherent detection system using a pilot symbol" is proposed as a method for carrying out coherent detection by compensating the phase of information symbols on the receiving side.

20 The coherent detection system using a pilot symbol is a method for carrying out coherent detection by estimating fluctuations in the phase of information symbols using pilot symbols (pilot bits) whose phase is known periodically (for example, every 1.25 ms) inserted in an information signal and compensating the phase of the information symbols through interpolation.

25 More specifically, the coherent detection system using a pilot symbol repeats an operation consisting of comparing the phase of a demodulated pilot symbol with an ideal phase (original phase) of the pilot symbol and

0926241-092601  
108260-1429260

calculating the phase error over a plurality of slots,  
and determines the phase of the information symbol between  
neighboring pilot symbols from the phase error  
calculation result through interpolation and thereby  
5 carries out coherent detection.

The coherent detection system using a pilot symbol  
is described, for example, in "Wideband CDMA Open-Air  
Transmission Result (RCS97-3)".

FIG.6 shows a configuration example of a reception  
10 signal.

A plurality of pilot symbols (pilot bits) 140, 150,  
160 and 170 in FIG.6 are known symbols inserted for every  
slot.

Detection target slot 2001 is a 1-slot information  
15 symbol to be detected. To compensate the phase of this  
1-slot information symbol, the amount of phase  
fluctuation is estimated using pilot symbols over a few  
slots before and after the detection target slot.

For example, suppose a signal in the configuration  
20 shown in FIG.6 is being received continuously. Suppose  
a case where coherent detection is performed using a  
plurality of pilot symbols 140 to 170. In this case, the  
information symbol which is the target of coherent  
detection is information symbol 2001 (that is, the  
25 detection target slot), two slots ahead of slot 2003  
currently being received.

Thus, it is necessary to temporarily store the  
previously received information symbols (information

0926241-092801  
TOP SECRET

symbols up to the one two slots ahead) until the estimation of phase fluctuation using pilot signals (pilot symbols) over a plurality of slots is completed.

That is, a coherent detection circuit requires a  
5 memory capable of storing symbols corresponding to at  
least 3 slots.

On the other hand, a CDMA communication system allows multi-code transmission to speed up communications of large volume image data, etc.

10           Multi-code transmission is a data transmission system intended to effectively use code resources by changing the number of codes to be multiplexed according to the amount of data.

For example, when sound data or a small-volume packet  
15 is transmitted, data is transmitted with one spreading  
code assigned to one physical channel.

On the other hand, when large-volume data such as a motion picture is sent, the motion picture data is divided into a plurality of physical channels, each physical channel is assigned one spreading code and those divided physical channels are multiplexed to carry out data transmission.

Multi-code transmission does not always use all codes, but dynamically determines codes to be used according to the situation. However, it is necessary to secure the memory area necessary to carry out the above-described coherent detection using a pilot symbol assuming the case where all channels are used.

There are various ways of memory configurations and it goes without saying that it is advantageous in every aspect of the area occupied, power consumption and ease of control, etc. to provide a common memory and control the memory in a concentrated manner rather than providing a plurality of memories and controlling them individually.

However, the following problem may arise in the case where electrically continuous memory areas large enough to store all reception data are provided for when the number of multiplexed channels reaches a maximum in order to be able to respond to dynamic changes in the number of multi-codes.

That is, since the same memory area is accessed regardless of the number of multiplexed codes, the entire memory area becomes the access target even in the case where data is transmitted with one code or where a plurality of codes is multiplexed. As a result, power consumption of the memory circuit always remains unchanged.

Further, in coherent detection using a plurality of pilot symbols over a plurality of slots, memory accesses occur when the information symbol of a slot currently being received is written and the information symbol of a detection target slot is read. That is, it is not necessary to generate memory accesses for other slots.

However, in the symbol storage memory configuration of a conventional coherent detection circuit, memory areas are electrically continuous, and therefore even

the memory area which need not be accessed may also be accessed and power is wasted accordingly.

The present invention is implemented based on such consideration and it is an object of the present invention to attain low power consumption in a memory circuit and coherent detection circuit.

#### Disclosure of Invention

The memory circuit of the present invention divides a memory area for strong information symbols into a plurality of electrically separated memory blocks based on at least one of information on the number of multi-codes and slot information.

Then, the memory circuit of the present invention carries out a data write or data read on each of the plurality of memory blocks periodically.

Blocks not subject to any data write or data read are set to a low power consumption mode.

With such a configuration, only necessary memory blocks become access targets first, which reduces the load on the driver and reduces power consumption. Furthermore, forcibly setting memory blocks which need not be accessed to a low power consumption mode (for example, stopping the supply of an operating clock and setting a non-operating state) further enhances the effect of reducing power consumption.

A mode of the memory circuit of the present invention delimits the memory area of the information symbol storage

0952241 0952250 1052260 1152270 1252280 1352290 1452300 1552310 1652320 1752330 1852340 1952350 2052360 2152370 2252380 2352390 2452400 2552410 2652420 2752430 2852440 2952450 3052460 3152470 3252480 3352490 3452500 3552510 3652520 3752530 3852540 3952550 4052560 4152570 4252580 4352590 4452600 4552610 4652620 4752630 4852640 4952650 5052660 5152670 5252680 5352690 5452700 5552710 5652720 5752730 5852740 5952750 6052760 6152770 6252780 6352790 6452800 6552810 6652820 6752830 6852840 6952850 7052860 7152870 7252880 7352890 7452900 7552910 7652920 7752930 7852940 7952950 8052960 8152970 8252980 8352990 8453000 8553010 8653020 8753030 8853040 8953050 9053060 9153070 9253080 9353090 9453100 9553110 9653120 9753130 9853140 9953150

memory for every code number of multi-code communication and divides it into a plurality of memory blocks. Then, by taking measures such as stopping a clock supply to memory blocks storing information symbols that need not  
5 be written or read, the memory circuit of the present invention reduces power consumption.

Furthermore, another mode of the memory circuit of the present invention electrically delimits the memory area for every reception slot and divides it into a  
10 plurality of memory blocks. Then, the memory circuit individually generates write access or read access to the memory block corresponding to the detection target slot and the memory block corresponding to the slot currently being received.

15 Furthermore, the coherent detection circuit of the present invention includes the memory circuit of the present invention, an interpolation section that corrects the phases of information symbols through interpolation and a coherent detection section. Since memory power  
20 consumption is reduced, power consumption of the coherent detection circuit is also reduced.

A mode of the coherent detection circuit of the present invention electrically delimits the memory area of the symbol storage memory incorporated in the coherent  
25 detection section for every multiplexed code and divides it into a plurality of memory blocks. The coherent detection circuit then operates only memory blocks in response to the dynamically variable number of codes.

0923241 0923241  
100260 1429260

When the number of codes used is small, the coherent detection circuit forcibly sets memory blocks not in used to a low power consumption mode by stopping the supply of the operating clock, etc. Low power consumption of the circuit is attained in this way.

#### Brief Description of Drawings

FIG.1 is a block diagram showing an overall configuration of an embodiment of a coherent detection circuit of the present invention;

FIG.2 is a block diagram showing a configuration of a receiver using the coherent detection circuit of the present invention;

FIG.3A illustrates features of a configuration of a memory circuit (symbol storage memory) of the present invention;

FIG.3B illustrates a sequence of write accesses and read accesses of the memory circuit (symbol storage memory) of the present invention;

FIG.4A is a block diagram showing a configuration example of the memory circuit (symbol storage memory) of the present invention;

FIG.4B is a circuit diagram showing a configuration example of the memory circuit (symbol storage memory) of the present invention integrated on a single semiconductor chip;

FIG.5 is a flow chart showing a characteristic operation of the memory circuit of the present invention;

093644-092804  
108260-4429260

and

FIG.6 illustrates a format example of a reception signal used to carry out coherent detection using a pilot symbol.

5

#### Best Mode for Carrying out the Invention

With reference now to the attached drawings, an embodiment of the present invention will be explained in detail below.

(Embodiment 1)

FIG.1 is a block diagram of a coherent detection circuit according to Embodiment 1 of the present invention. FIG.2 is a block diagram showing a configuration of a CDMA receiver (RAKE combining) using the coherent detection circuit of the present invention.

First, an overall configuration of the CDMA receiver will be explained.

As shown in FIG.2, a CDMA receiver includes reception antenna 7, high frequency signal processing section 8, A/D conversion section 9 that converts an analog signal to digital signal, despreading section 10 that despreads the reception signal at predetermined timing and demodulates data, coherent detection section 11 that carries out coherent detection on the despread data, RAKE combining section 12 that RAKE-combines signals subjected to despreading and coherent detection corresponding to a plurality of paths, channel CODEC section 13 that carries



out channel decoding and multi-code number information extraction section 14 and despreading code generation section 15.

Despreading section 10 is provided with a plurality  
5 of reception fingers 16a to 16n and searcher 17.

Multi-code number information extraction section 14 extracts information indicating the number of codes inserted in the reception signal and in use and gives this information to coherent detection section 11.

10 Furthermore, despreading code generation section 15 generates, for example, three despreading codes C0 to C2 and supplies these codes to despreading code generation section 15.

A reception signal is demodulated to a baseband  
15 signal at high frequency signal processing section 8, A/D-converted to digital data and then input to despreading section 10.

At despreading section 10, the reception signal is subjected to despreading processing by a plurality of  
20 despreaders and the data is demodulated. The despreaders are determined taking into account the number of multi-paths and the number of multiplexed codes, etc.

Coherent detection section 11 and RAKE combining section 12 compensate the plurality of data items for  
25 the phases of multi-paths for every code and carry out RAKE combining.

Next, a configuration and operation of coherent detection section 11 will be explained with reference

0926341 092660  
T02250 T4292660

Dividing the memory area into a plurality of blocks

allows only necessary blocks to be accessed.

That is, separating the word lines from the bit lines reduces the load on the drivers (word line driver and bit line driver) necessary for memory accesses and reduces the amount of charging/discharging current, making it possible to reduce power consumption.

In addition, forcibly stopping the supply of the operating clock to unused memory blocks makes the main circuit of the relevant block operate in a low power consumption mode. This also reduces the operating current of the circuit, further reducing power consumption.

Memory interface section 17 is a kind of address decoder and determines which address of which memory block should be accessed.

Memory operation control section 3 selects memory blocks to be activated and memory blocks to be set to a low power consumption mode as appropriate, outputs control signals and controls the operating modes of memory blocks.

Memory operation control section 3 is fed with information on the multiplexed code numbers (MCN) output from multi-code number information extraction section 14 in FIG.2.

Memory operation control section 3 selects only the memory block line (traverse line) corresponding to the code (multiplexed code) actually being used and deselects other memory block lines.

0922641-0922601  
108260-14292660

The selected memory block line is periodically accessed in a predetermined sequence. A specific operating procedure thereof will be described later.

Furthermore, phase estimation section 5 extracts pilot signals inserted at one-slot intervals from each reception signal and estimates the phases of pilot signals on the phase plane (channel estimation).

Interpolation section 6 determines the phase of an information symbol between two neighboring pilot signals through interpolation.

Coherent detection circuit 16 carries out coherent detection on information symbols read from memory blocks at timing corresponding to the phases corrected through interpolation.

The signal subjected to coherent detection is given to RAKE combining section 12.

An overall operation of the coherent detection circuit in FIG.1 will be explained more specifically.

Despread information symbols  $f_0$  to  $f_{n-1}$ ,  $f_n$  to  $f_{2n-1}$ ,  $f_{2n}$  to  $f_{3n-1}$  are information corresponding to code 1, code 2 and code 3, respectively.

Data corresponding to each code includes  $n$  signals from path (0) to path ( $n-1$ ). Signals of different paths have the same information content but have different amounts of delay. Delay differences are on the order of several chips.

Despread information symbols  $f_0$  to  $f_{n-1}$ ,  $f_n$  to  $f_{2n-1}$ ,  $f_{2n}$  to  $f_{3n-1}$  are each assigned specific address numbers

The number of addresses of information symbols  $f_0$  to  $f_{n-1}$ ,  $f_n$  to  $f_{2n-1}$ ,  $f_{2n}$  to  $f_{3n-1}$  is equal to the number of symbols mapped within one slot of the channel received.

Memory interfaces 1a to 1c in FIG.1 are each fed with despread information symbols  $f_0$  to  $f_{n-1}$ ,  $f_n$  to  $f_{2n-1}$ ,  $f_{2n}$  to  $f_{3n-1}$  of the same code. That is, despread information symbols for every path to be subjected to RAKE combining are input.

On the other hand, the information symbol data stored for a period of time corresponding to 2 slots is selected by selector 4 and sent to coherent detection circuit 16.

Then, with reference to FIG.3A, FIG.3B, FIG.4A and

As shown in FIG.3A, the memory area for storing information symbols is divided into three memory block lines (L1 to L3) for the respective codes in order to respond to the case where the code multiplexing number is "3".

As a result of such memory area divisions, 9 electrically independent memory blocks 2a to 2i are formed.

Then, the procedure for accessing each memory block will be explained using FIG.3B.

\_\_\_\_\_

When the number of codes is "1", slot number "1" is assigned to a plurality of portions of data (f0 to fn-1) with different amounts of delay about the information symbol of the first despread slot and the respective portions of data are written to memory block 2a. This state is "state 1".

Then, likewise, slot number "2" is assigned to a plurality of portions of data (f0 to fn-1) with different amounts of delay about the information symbol of the second slot and the data is written to memory block 2b. This

15 state is "state 2".

The information symbol data read in state 3 is sent to coherent detection circuit 16 in FIG.1.

Slot number "1" is assigned to the fourth slot data again and the data is overwritten to memory block 2a whose read has been completed. At the same time, the data about the information symbol stored two slots ahead is read from memory block 2b and sent to coherent detection circuit 16 in FIG.1. This state is "state 4".

Likewise, the process moves on to state 5 and then state 6. Since state 6 is the same as state 3, the process moves on to state 4 after state 6, and state 4, state 5 and state 6 appear repeatedly thereafter.

5        Thus, data is written for every slot, in the order of memory block 2a, 2b and 2c. After a write to memory block 2c is completed, the process returns to memory block 2a and a write is performed sequentially again and this procedure is repeated.

10       On the other hand, information symbol data is read starting from the memory block for which a write has completed two slots ahead relative to the memory block currently being written.

15       As is apparent from FIG.3B, not more than two of the three memory blocks operate in the memory block line corresponding to one code in each of states 1 to 6, and therefore there are always memory blocks which need not be operated.

20       That is, accesses to memory blocks are generated only when information of the "detection target slot" is read and when information of the "slot currently being received" is written.

25       Therefore, setting memory blocks which need not be operated to a low power consumption mode makes it possible to reduce power consumption. The low power consumption mode of a memory block is implemented by, for example, stopping a clock supply to drive the word lines or bit lines.



The configuration of the present invention can implement operations ① to ④ below.

① It is possible to control so as to prevent write access and read access to a same memory block from occurring simultaneously.

② It is possible to carry out write access and read access to a memory block periodically.

③ It is possible to set a low power consumption mode (non-operating mode) for memory blocks to which no access is generated by stopping the circuit operation or stopping operation of part of the circuit.

That is, it is possible to prevent accesses to memory cells making up the SRAM from being generated. This reduces power consumption to at least two thirds of conventional power consumption.

④ Furthermore, in the example above, only the memory block line corresponding to code 1 (L1 in FIG.3A) operates and memory block lines L2 and L3 corresponding to code 2 and code 3 do not operate at all. This can completely stop the operations of memory blocks 2d to 2i that belong to memory block lines L2 and L3.

In this case, as is apparent from FIG.3A, too, it is only two of the 9 physically (electrically) delimited memory blocks that operate and other memory blocks do not operate.

Therefore, when the number of codes is 1, if power consumption is compared simply focused on the operation ratio, the present invention can reduce power consumption

0925241.092503

to two-ninths of the conventional configuration.

Thus, the present invention makes it possible to effectively reduce power consumption of the memory circuit for storing information symbols.

5        Then, the case where the number of multiplexed codes is "2" will be explained.

10        In this case, memory block lines L1 and L2 operate for code 1 and code 2 respectively and memory block line L3 does not operate. Thus, it is possible to stop the operation of memory block line L3.

15        Thus, it is 4 of the 9 physically (electrically) delimited memory blocks that operate simultaneously and if power consumption is compared simply focused on the operating ratio, the present invention can reduce power consumption to four-ninths of the conventional configuration.

20        Likewise, when the number of multiplexed codes is "3", write or read operations occur in all memory block lines L1 to L3. Thus, it is 6 of the 9 physically (electrically) delimited memory blocks that operate simultaneously and if power consumption is compared simply focused on the operating ratio, the present invention can reduce power consumption to six-ninths of the conventional configuration.

25        FIG.4A and FIG.4B show specific configuration examples of memory blocks (for example, 2a to 2c).

Control of switching between operation/non-operation of a plurality of memory blocks

FIG.4B shows a specific circuit configuration. In FIG.4B, memory blocks 2a to 2c are integrated on a single chip. The word lines (wl to wn, wl' to wn", wl" to wn") of the respective memory blocks are electrically separated. Likewise, the bit lines are also driven independently.

The configuration and operation of memory block 2a  
15 will be explained below.

Then, drivers (a1 to a2n, b1 to bm) are controlled by drive circuits (30a to 30c) for the respective memories. Therefore, it is possible to individually control active/non-active of each memory by controlling a clock supply at each drive circuit.

As shown above, it is possible to reduce power consumption to two-ninths to six-ninths of that of the memory circuit of the conventional coherent detection circuit by delimiting physically (electrically) the memory area for information symbol storage based on the number of multiplexed codes and slot number.

In the above explanations, the number of multiplexed codes is assumed to be "3", but the present invention is not limited to this. The effect of reducing power consumption of the present invention is enhanced as the  
5 number of multiplexed codes increases.

Moreover, in the above explanations, the number of information symbol slots stored is assumed to be 3 slots, but the present invention is not limited to this.

The CDMA receiver shown in FIG.2 has coherent  
10 detection section 11 with reduced power consumption, and therefore is suited to LSI implementation. Furthermore, it also allows cellular phone batteries to last longer.

As described above, the characteristic operations of the memory circuit of the present invention can be  
15 summarized in FIG.5.

A memory for storage of information symbols is divided into a plurality of electrically separated (electrically independent) blocks based on at least one of the information on the number of multi-codes and slot  
20 information beforehand (step 50).

Then, data write and data read are carried out on each of the plurality of blocks periodically while controlling access timing so that write access and read access do not occur simultaneously. Blocks subject to  
25 neither data write nor data read are forcibly set to a low power consumption mode (step 51).

Thus, the present invention can minimize power consumption associated with memory accesses by dividing

092224-092204  
108260-1429260

a memory area into a plurality of blocks and individually  
controlling operations of the respective blocks. Thus,  
the present invention allows cellular phone batteries  
to last longer even if communications of large-volume  
5 data such as moving pictures are carried out.

This application is based on the Japanese Patent  
Application No. 2000-026306 filed on February 3, 2000,  
entire content of which is expressly incorporated by  
10 reference herein.

#### Industrial Applicability

The present invention can be applied to a memory  
circuit or coherent detection circuit mounted on a CDMA  
15 receiver.

09225244.0922504  
09225244.0922504